

LTE FILTERS

FI 686 · FI 680

Lte2

- √ Saw filter (FI 686)
- √ Low passband insertion loss
- √ Great rejection in bands Lte2 and Lte1
- √ Reversible input / output
- √ Cylindrical box for better connection

Ek

EKSELANS BY ITS



FI 686



FI 680

TECHNICAL TABLE

REFERENCE		FI 686	FI 680
Code		031027	031029
Passband	MHz	5 - 694	5 - 686
Technology		SAW	-
Insertion loss	dB 5-678 MHz dB 686 MHz dB 694 MHz dB 703 MHz	<3 <5 >8 >25	<2 <5 >12 >25
Rejected band	MHz	695-862	695-862
Connectors		1x F Female 1x F Male	1x F Female 1x F male
Passage of current	mA	100	100
Typical use		Indoor	Indoor